Features

- Current transfer ratio (CTR: 50~600% at IF =5mA, VCE = 5V)
- High isolation voltage between input and output (Viso =3750Vrms)
- Collector - emitter breakdown voltage BVCEO ≥ 80V
- Operating Temperature: -55 ~110
- Environmentally friendly products, compliant with CQC, UL, and VDE requirements

Mechanical Data

- Case: SOP4
- Molding Compound: UL Flammability Classification Rating 94V-0
- Terminals: Matte tin-plated leads; solder ability-per MIL-STD-202, Method 208

Applications

- It is widely used in the feedback control loop of switching power supply and the isolation between the main circuit and the control circuit, ensuring the stability of the output voltage and quickly transmitting the fault signal to trigger the protection mechanism in the case of overload or short circuit.
- In applications such as PLCs (Programmable Logic Controllers), motor drives, and sensor interfaces, it is used for signal isolation to prevent high-voltage noise from interfering with low-voltage control logic.
- For signal isolation in serial communication interfaces (e.g., RS-232,) to improve anti-interference capability.
- Consumer electronics: household appliances, smart home devices (smart lighting, smart sockets), computers and peripherals (printers, monitors), etc.
- Lighting control: AC transistor optocoupler is suitable for dimming control, smart switching, and

Photo transistor

XL856

XINGLIGHT

Photo transistor

XL356

XL356

XINGLIGHT

Photo transistor

XL356

Photo tr×

XL356

Photo transistor

XL356

XINGLIGHT

Photo transistor

XL356