



目录

电性参数

典型特性曲线

可靠性实验

外形尺寸

包装

焊接指导

使用注意事项

















焊接指导 (1)

Guideline for Solder

伸入 鉄入



W

300

i di

3

LED t ^ z

Manual welding is recommended only for separate industry situations. A soldering iron of less than 30W is recommended to be used in Hand Soldering. Please keep the temperature of the soldering iron under 300 while soldering. Each terminal of the LED is to go for less than 3 second and for one time only.

Be careful because the surface of the product is 1mm "



使用注意事项 (1)

Precautions (1)

贮存:

Moisture proof and anti-electrostatic package with moisture absorbent material is used, to keep moisture to a minimum.

$$\delta \leq \%RH$$

Before opening the package, the product should be kept at 3 °C or less and humidity less than 6 %RH, and be used within a year.

$$3 \leq 1 \text{ RH} \leq 16 \text{ RH}$$

$$3 \leq 6 \text{ RH} \leq \%$$

After opening the package, the product should be stored at 3 °C or less and humidity less than 16 RH, and be soldered within 16 hours (7 days). It is recommended that the product be operated at the workshop condition of 3 °C or less and humidity less than 6 RH. $\leq \%$

LED

$$\leq 5 \leq 2 \text{ hours} \leq \%$$

If the moisture absorbent material has fade away or the LEDs have exceeded the storage time, baking treatment should be performed based on the following condition: (6 ± 5) °C for 2 hours. $\leq \%$

静电:

Static electricity or surge voltage damages the LEDs. Damaged LEDs will show some unusual characteristic such as the forward voltage becomes lower, or the LEDs do not light at the low current, even not light.

All devices, equipment and machinery must be properly grounded. At the same time, it is recommended that wrist bands or anti-electrostatic gloves, anti-electrostatic containers be used when dealing with the LEDs.



